



**APPLICATION NOTE**

Cage Code:  06324	Document Description APPLICATION NOTE Design & Installation of El Ochito PCB Connectors	Document #: AN0002 Revision: A Page 1 of 6
-------------------------	---	--

**APPLICATION NOTE**  
**Design & Installation of El Ochito PCB Connectors**

WRITTEN BY: \_\_\_\_\_ DATE: \_\_\_\_\_  
 Bryan Samowitz

APPROVED BY: \_\_\_\_\_ DATE: \_\_\_\_\_  
 Guido Hunziker

THIS COPYRIGHT DOCUMENT IS THE PROPERTY OF GLENAIR INC. AND IS FURNISHED ON THE EXPRESS CONDITION IT IS NOT TO BE DISCLOSED, PRODUCED IN WHOLE OR PART, OR USED TO SOLICIT QUOTATIONS FROM COMPETITIVE SOURCES, OR USED FOR MANUFACTURE BY ANYONE OTHER THAN GLENAIR INC. WITHOUT THE WRITTEN PERMISSION OF GLENAIR INC. THE INFORMATION HEREIN HAS BEEN DEVELOPED AT PRIVATE EXPENSE AND MAY BE USED FOR THE PURPOSES OF ENGINEERING EVALUATION AND FOR INCORPORATION INTO TECHNICAL SPECIFICATIONS AND OTHER DOCUMENTS WHICH SPECIFY PROCUREMENT OF PRODUCTS FROM GLENAIR INC.



1211 AIRWAY, GLENDALE, CALIFORNIA 91201

**APPLICATION NOTE**

**Design & Installation of El Ochito PCB Connectors**

CODE NUMBER 06324	SIZE A	<b>AN0002</b>	REV. A
SCALE N/A		SHEET 1 OF 6	

Cage Code: 06324	Document Description APPLICATION NOTE Design & Installation of El Ochito PCB Connectors	Document #: AN0002 Revision: A Page 2 of 6
---------------------	---	--

## REVISION HISTORY

REVISION	DATE	REVISED PAGES	REVISIONS
A	8/19/2019		Initial Release

Cage Code:  06324	Document Description APPLICATION NOTE Design & Installation of El Ochito PCB Connectors	Document #: AN0002 Revision: A Page 3 of 6
-------------------------	---	--

## Table of Contents

1.0	Purpose .....	4
2.0	Referenced Documents .....	4
3.0	Responsibility .....	4
4.0	Methods of Performance Optimization.....	5
4.1	PCB Layout & Design .....	5
4.2	Installation onto Board.....	6
4.3	Trace Routing .....	6
4.4	Other Considerations .....	6

## Table of Figures

Figure 1 – Optimized PCB Layout.....	5
Figure 2 – Optimized PCB Cross Section .....	5

Cage Code: 06324	Document Description APPLICATION NOTE Design & Installation of El Ochito PCB Connectors	Document #: AN0002 Revision: A Page 4 of 6
---------------------	---	--

## 1.0 Purpose

This document describes the proper way to design and install El Ochito PCB connectors & contacts onto a PCB.

Deviating from the methods described herein will result in lesser performance.

## 2.0 Referenced Documents

Document Number/Name	Description
233-218 & similar	SuperNine El Ochito PCB Connectors
792-007/008, 792-009/010, & similar	Series 792 PCB Connectors
882-005, 882-008, 882-017, & similar	SuperFly DataLink PCB Connectors
806-039/040 & similar	Mighty Mouse 806 El Ochito PCB Connectors
801-120 & similar	Mighty Mouse 801 El Ochito PCB Connectors
805-126 & similar	Mighty Mouse 805 El Ochito PCB Connectors
858-011, 858-034, 858-036, & similar	ARINC 600 El Ochito PCB Contact
858-025	El Ochito Transition Adaptor

**Table 1. Reference Documents**

## 3.0 Responsibility

This document is the responsibility of the Engineering team.

## 4.0 Methods of Performance Optimization

### 4.1 PCB Layout & Design

To achieve optimal impedance matching at the PC tail/PCB transition, we recommend the follow layout:




Figure 1 – Optimized PCB Layout




Figure 2 – Optimized PCB Cross Section

Cage Code: 06324	Document Description APPLICATION NOTE Design & Installation of El Ochito PCB Connectors	Document #: AN0002 Revision: A Page 6 of 6
---------------------	---	--

## 4.2 Installation onto Board

Trim the PC tails to a length of .020 inches or less per figure 2. This minimizes the length of capacitive stubs, which lower impedance and cause the signal to resonate.

## 4.3 Trace Routing

Route the traces for the high-speed lines on the opposite side of the PCB from the connector, which further reduces the length of capacitive stubs.

The signal trace width needed for the desired impedance is dependent on the PCB Stack-up, PCB material, and whether the traces are routed as differential pairs or single-ended lines.

## 4.4 Other Considerations

When being used in a connector that does not have PCB stand-offs, design for the PCB to be .020 inches from the base of the El Ochito PCB per figure 2.