






SERIES 28 HiPer-D® Combo Connectors






Reference and Technical Data

Combo HiPer-D® power, signal and RF contact arrangements



Mating face of pin connector. Socket connector numbers are reversed.




Arrangement	1-2W2	1-5W1	2-3W3	2-7W2	2-11W1
Shell Size	1	1	2	2	2
Contacts	2 #8	4 #20, 1 #8	3 #8	5 #20, 2 #8	10 #20, 1 #8




Arrangement	3-13W3	3-17W2	3-21W1	3-5W5
Shell Size	3	3	3	3
Contacts	10 #20, 3 #8	15 #20, 2 #8	20 #20, 1 #8	5 #8




Arrangement	3-9W4	4-13W6	4-17W5
Shell Size	3	4	4
Contacts	5 #20, 4 #8	7 #20, 6 #8	12 #20, 5 #8





Arrangement	4-21WA4	4-25W3
Shell Size	4	4
Contacts	17 #20, 4 #8	22 #20, 3 #8



Arrangement	4-27W2	4-8W8
Shell Size	4	4
Contacts	25 #20, 2 #8	8 #8



Arrangement	5-24W7	5-36W4
Shell Size	4	5
Contacts	17 #20, 7 #8	32 #20, 4 #8



Arrangement	5-43W2	5-47W1
Shell Size	5	5
Contacts	41 #20, 2 #8	46 #20, 1 #8